

Wireless RS232 Interface Board

TDi2 interface board enables a cable free transparent data link between RS232 ports without any additional interface circuitry.




Figure 1: TDi2-433-9

The interface board features an on-board TDL2A-433-9 OEM serial modem, MAX232 RS232 driver, 9 way D connector, 5V voltage regulator and SMA RF connector, hence requires just a Voltage supply to power up and operate without any additional interface circuitry. The TDL2A modules would be soldered directly on to the interface board for better grounding and to improve RF performance. The helical antenna and the SMA connector shown are optional. User could also use a two pin terminal block instead to mount a 1/4 whip antenna made of piece of wire or metal rod.

Features

- RS232 driver and DB9F connector for direct interface to PC serial port
- Serial modem baud rate at 9600bps (half-duplex)
- Addressable point-to-point
- 5 serial select wideband channels
- Carries ASCII and RTU MODBUS messages
- Access to internal diagnostic/Test modes using HyperTerminal
- On board SMA antenna connector
- Signal LED for visual indication of valid code received
- Setup is simple as Plug-and-Play
- Set-up and configuration using HyperTerminal
- Size: 61mm x 33mm (excluding helical antenna length of 55mm)

Technical Summary

- Operating frequency: 433.925MHz (default)
- Modulation: 16kbps bi-phase FSK
- Supply range: 5 - 15V @ 28mA (transmit), 22mA (receive)
- Transmit power: +10dBm (10mW)
- Receiver sensitivity: -107dBm (for 1% BER)
- 32 byte data buffer
- Adjacent channel rejection: 65db @ ± 320 kHz
- Receiver Blocking: 84dB
- Conforms to EN 300 220-2 (radio) and EN 301 489-3 (EMC)
- Line of sight operating range: 200-300m

Configuring the TDi2

In order to use all the functions embedded in the on board TDL2A modem, the user must be aware of the setup /programming facility, which allow different addresses and frequency channels to be set up, and if necessary accesses diagnostic test modes.

The TDi2 is programmed through the same RS232 port that is used for sending/receiving data. An RS232 terminal emulator (such as Aterm or HyperTerminal) is an ideal tool.

Connect the TDi2 directly (or via serial straight through cable) to the PC serial port.

To enter program mode, insert the PGM jumper (to pull the SETUP pin of TDL2A low) and run the PC HyperTerminal program. In this mode the radio link is disabled, but characters sent (at 9600 baud, as normal) to the unit are echoed back on the RXD pin.

The HyperTerminal should be set with the following settings.

9600 baud RS232, 8 bit data, no parity, 1 start bit, 1 or 2 stop bits. No flow control.

The unit will only respond to certain command strings:

ADDR0 to ADDR7 <CR><LF> These commands set up one of 8 unique addresses. A TDi2 will only communicate with a unit set to the same address.

CHAN0 to CHAN4 <CR><LF> These commands select one of 5 preset channels

A TDi2 will only communicate with a unit set to the same address and the same channel.

Address and channel numbers are stored in volatile memory. On power-up the TDi2 reverts to the default in EEPROM (as supplied this is always address 0 and Channel 0)

SETPROGRAM <CR> Writes the current set address into EEPROM as the new default.
A tilde character (~, ascii 126dec) sent by the unit indicates end of EEPROM write sequence

(these commands are normally only used for factory diagnostics)

NOTONE <CR> Transmit unmodulated carrier

LFTONE <CR> Transmit carrier modulated with 8KHz squarewave

HFTONE <CR> Transmit carrier modulated with 16KHz squarewave

<CR> Transmitter off

A Carriage Return '<CR>' (00Dhex) should be entered after each command sequence to execute it. Releasing the SETUP (by removing the PGM jumper) to high state returns the TDi2 to normal operation




Figure 2: Schematic diagram of TDi2




Figure 3: PCB layout of TDi2 (bottom view)

On-board regulator (L4931) can supply up to 250mA current at 5V.

R9 (LK1) connects pin 9 (Ring Indicator) on the D type to the 5V, which enables any external host to be powered from pin 9 (+5V DC) and pin 5 (GND). Certain CCD barcode scanner can make use of this feature, eliminating the need for additional external power adaptor.

R8 connects STATUS (data ready, via an RS232 buffer) to DCD, DSR and CTS. Not linking this jumper (LK2 at the back of the board) saves power.

The SIG LED is provided for visual indication of STATUS data ready. This LED would lit when a valid data is present in the receive buffer.

Radiometrix Ltd

**Hartcran House
231 Kenton Lane
Harrow, Middlesex
HA3 8RP
ENGLAND**

**Tel: +44 (0) 20 8909 9595
Fax: +44 (0) 20 8909 2233
sales@radiometrix.com
www.radiometrix.com**

Copyright notice

This product data sheet is the original work and copyrighted property of Radiometrix Ltd. Reproduction in whole or in part must give clear acknowledgement to the copyright owner.

Limitation of liability

The information furnished by Radiometrix Ltd is believed to be accurate and reliable. Radiometrix Ltd reserves the right to make changes or improvements in the design, specification or manufacture of its subassembly products without notice. Radiometrix Ltd does not assume any liability arising from the application or use of any product or circuit described herein, nor for any infringements of patents or other rights of third parties which may result from the use of its products. This data sheet neither states nor implies warranty of any kind, including fitness for any particular application. These radio devices may be subject to radio interference and may not function as intended if interference is present. We do NOT recommend their use for life critical applications.

The Intrastat commodity code for all our modules is: 8542 6000

R&TTE Directive

After 7 April 2001 the manufacturer can only place finished product on the market under the provisions of the R&TTE Directive. Equipment within the scope of the R&TTE Directive may demonstrate compliance to the essential requirements specified in Article 3 of the Directive, as appropriate to the particular equipment.

Further details are available on The Office of Communications (Ofcom) web site:

<http://www.ofcom.org.uk/>

Information Requests

Ofcom

Riverside House

2a Southwark Bridge Road

London SE1 9HA

Tel: +44 (0)300 123 3333 or 020 7981 3040

Fax: +44 (0)20 7981 3333

information.requests@ofcom.org.uk

European Communications Office (ECO)

Pebblinghus

Nansensgade 19

DK 1366 Copenhagen

Tel. +45 33896300

Fax +45 33896330

ero@ero.dk

www.ero.dk
