

Wireless RS232 Interface Board

TDi2 interface board enables a cable free transparent data link between RS232 ports without any additional interface circuitry.




Figure 1: TDi2-433-9

The interface board features an on-board TDL2A-433-9 OEM serial modem, MAX232 RS232 driver, 9-way D connector, 5V voltage regulator and SMA RF connector, hence requires just a voltage supply to power up and operate without any additional interface circuitry. The TDL2A modules would be soldered directly on to the interface board for better grounding and to improve RF performance. The helical antenna and the SMA connector shown are optional. User could also use a two-pin terminal block instead to mount a 1/4 whip antenna made of a piece of wire or metal rod.

Features

- RS232 driver and DB9F connector for direct interface to PC serial port
- Serial modem baud rate at 9600bps (half-duplex)
- Addressable point-to-point
- 5 serial select wideband channels
- Carries ASCII and RTU MODBUS messages
- Access to internal diagnostic/Test modes using HyperTerminal
- On-board SMA antenna connector
- Signal LED for visual indication of valid code received
- Supply range: 5 - 15V @ 28mA (transmit), 22mA (receive)
- Setup is simple as Plug-and-Play
- Set-up and configuration using HyperTerminal
- Conforms to EN 300 220-3 and EN 301 489-3
- Size: 61mm x 33mm (excluding helical antenna length of 55mm)

Applications

- Handheld / portable terminals
- PDAs, organisers & laptops
- Industrial telemetry and telecommand
- In-building environmental monitoring and control
- Remote data acquisition system, data logging
- Fleet management, vehicle data acquisition




Figure 2: Schematic diagram of TDi2




Figure 3: PCB layout of TDi2 (bottom view)

On-board regulator (L4931) can supply up to 250mA current at 5V.

R9 (LK1) connects pin 9 (Ring Indicator) on the D type to the 5V, which enables any external host to be powered from pin 9 (+5V DC) and pin 5 (GND). Certain CCD barcode scanner can make use of this feature, eliminating the need for additional external power adaptor.

R8 connects STATUS (data ready, via an RS232 buffer) to DCD, DSR and CTS. Not linking this jumper (LK2 at the back of the board) saves power.

The SIG LED is provided for visual indication of STATUS data ready. This LED would lit when a valid data is present in the receive buffer.

Radiometrix Ltd

**Hartcran House
231 Kenton Lane
Harrow, Middlesex
HA3 8RP
ENGLAND**

**Tel: +44 (0) 20 8909 9595
Fax: +44 (0) 20 8909 2233
sales@radiometrix.com
www.radiometrix.com**

Copyright notice

This product data sheet is the original work and copyrighted property of Radiometrix Ltd. Reproduction in whole or in part must give clear acknowledgement to the copyright owner.

Limitation of liability

The information furnished by Radiometrix Ltd is believed to be accurate and reliable. Radiometrix Ltd reserves the right to make changes or improvements in the design, specification or manufacture of its subassembly products without notice. Radiometrix Ltd does not assume any liability arising from the application or use of any product or circuit described herein, nor for any infringements of patents or other rights of third parties which may result from the use of its products. This data sheet neither states nor implies warranty of any kind, including fitness for any particular application. These radio devices may be subject to radio interference and may not function as intended if interference is present. We do NOT recommend their use for life critical applications.

The Intrastat commodity code for all our modules is: 8542 6000

R&TTE Directive

After 7 April 2001 the manufacturer can only place finished product on the market under the provisions of the R&TTE Directive. Equipment within the scope of the R&TTE Directive may demonstrate compliance to the essential requirements specified in Article 3 of the Directive, as appropriate to the particular equipment.

Further details are available on The Office of Communications (Ofcom) web site:

<http://www.ofcom.org.uk/>

Information Requests

Ofcom

Riverside House

2a Southwark Bridge Road

London SE1 9HA

Tel: +44 (0)300 123 3333 or 020 7981 3040

Fax: +44 (0)20 7981 3333

information.requests@ofcom.org.uk

European Communications Office (ECO)

Pebblinghus

Nansensgade 19

DK 1366 Copenhagen

Tel. +45 33896300

Fax +45 33896330

ero@ero.dk

www.ero.dk
